

RW Audio

Magnepan LRS+ Stand

Recommended Filament: PLA

Alternate: PETG

Support required: No

Brim required: Yes

Layer Height: 0.2-0.3mm

Perimeters: 2-3

Infill: 15-25%

Print orientation: Laying on it's side with "RW Audio" readable, rotate 293 degrees and place within build envelope for Bambu printers

Optional accessories: 8x M8 Spike with Insert

<https://solen.ca/en/products/solen-ss901-speaker-spike-copper-nickel-black-m8>

Or

<https://solen.ca/en/products/solen-ss907-speaker-spike-copper-nickel-black-m8>

Original items required: 8x factory mounting bolts are reused to attach stands to speakers

Download from: <http://www.rwaudio.com/free-downloads>

Buy me a coffee: <https://www.buymeacoffee.com/rwaudio7>

